

Wireless Magnetic Door Switch



PART NUMBER: 3503

FEATURES

- Sends wireless signal when a door or window is opened
- Built-in call button extends usage options - eg. use it as a portable panic button
- Double sided tape included for easy mounting
- Battery included
- LED alarm active indication

TECHNICAL SPECIFICATIONS

- Operating frequency: 433.92 MHz
- Typical operating range: 50 m*
- Power requirements: 3 V (CR2032 lithium)
- Dimensions of housing (L x W x D): 79 x 29 x 12 mm
- Dimensions of magnet (L x W x D): 60 x 12 x 7 mm
- Enclosure material: Durable ABS plastic
- Weight: 28 g
- Operating temp: 5°C to 40°C
- Rel humidity: < 90%

ACCESSORIES

3500 ActiveCare Console, **3501** ActiveCare Pager, **3508** LED Pager, **2544 & 2549** Wireless Multiport Expanders, **2700** Six Channel Cordless Monitor, **2501** LRCS Care Station, **2502** LRCS Zone Repeater

cura¹.com

*The range of wireless devices may vary and be dependent on your specific environmental conditions. cura¹ products are designed to augment well designed care programs and practices, cura¹ does not claim that any of its products are suitable as a substitute, or as a total solution for individuals that require care and constant supervision, and are at risk.